

録画再生時に 4 画面で再生すると 1 画面にリソース不足と表示されてしまう場合

30FPS に対応しているカメラを 4 台接続すると、録画再生時の画面数が最大で 3 画面になります

録画機の設定より録画している FPS 値を下げて頂くことで 4 画面再生が可能になります

分割画面よりマウスを右クリック

- ①「チャンネル」を左クリック
- ②「記録ストリーム」を左クリック
- ③「フレームレート」が 15 になっている場合が 10 まで下げます
- ④「適用」を左クリックして設定は完了です

※設定後の録画データから 4 画面同時再生が可能になります

The screenshot shows the XVR 5.0 interface with the following settings and actions highlighted:

- ①** The 'チャンネル' (Channel) dropdown menu is highlighted with a red box and the number 1.
- ②** The '記録ストリーム' (Record Stream) option in the left sidebar is highlighted with a red box and the number 2.
- ③** The 'フレームレート' (Frame Rate) slider is highlighted with a red box and the number 3, showing the value set to 10.
- ④** The '適用' (Apply) button at the bottom right is highlighted with a red box and the number 4.

Other visible settings include: Channel 1, Preview AHD 4MP30, Video Encoding H265, Audio Encoding G711U, H265+ disabled, Audio Input AIN, Encode Level Medium, Main Stream 4MP_LITE, Sub Stream CIF, Stream Type AudioVideo, Bitrate Type VBR, I-Frame Interval 2, Quality Good, Bitrate 806 Kb/S.